



Product Data Sheet

Neutrik NADITBNC-F

Description



The Neutrik NADITBNC-F is a female XLR chassis connector 110 Ω input - female BNC 75 Ω output. Interface balanced and coaxial lines.

Product	SKU
NEUTRIK NADITBNC-F	DB-00-512

Key Benefits

- Allow long cable runs for digital audio signals via low attenuation coax lines
- Match balanced to coaxial lines
- Match impedances 110 Ω to 75 Ω
- Simple to use, passive units



Product Data Sheet

Neutrik NADITBNC-F

Technical Specification

Neutrik NADITBNC-F Specification

Connection type: Adapter	Electrical
Gender: female	Frequency range: 0.1 - 6 MHz
	Rated voltage: ≤ 5 V p-p
	VSWR: < 1.1
	Return loss: > 26.4 dB
	Insertion Loss: < 0.3 dB @ 0.1 MHz to 10 MHz

Technical Drawing

